



### Standard Features

- Single Bearing Brushless Generator
- ± 1% Solid-State Voltage Regulation
- Low 1,800 RPM Operating Speed
- Safety Shutdown Systems
- Four Points isolation Mounts
- Automatic Low Oil Pressure and High Water Temperature
- Fresh Water Heat Exchanger Cooling
- Zinc Anode in Heat Exchanger
- Water Cooled manifold and Stainless Steel Exhaust Elbow
- Direct Drive Sea Water Pump
- Racor Fuel Filter - 2 Micron
- Air Intake Cleaner / Silencer
- Electric Fuel Transfer Pump
- Spin-On Lube Oil Filter
- 12 Volt Starting
- 12 Volt Battery Charging Alternator
- J-Can Electronic Control Panel
- Awl-Craft 2000 Urethane Finish
- 5 Year Limited Warranty

J6-99.0KW

### Specifications

- Kubota Model JD6-99.0KW
- Engine JOHN DEERE 6068TFM76 Tier 2
- Cubic Inch Displacement 414
- Bore x Stroke 4.19" x 5.00"
- Dimensions (LxWxH) 78.75" x 30" x 39.50"
- Weight (lbs.) 2700
- Output (volts) 208 Three Phase
- Output (amps) 275.2
- Output (watts) 99,000
- Oil Capacity 13qt (24.6 Liters)
- Fuel Consumption @ 50% Load 4.5 GPH
- Fuel Consumption @ 100% Load 7.7 GPH
- Exhaust Dia. 3.5"

### Optional Equipment

- Remote J-can electronic control panel with display for all engine and generator functions
- Stainless Steel Drip Pan
- Three phase generator output
- 24 Volt Starting System
- Dedicated motor starting generator windings
- Sound Attenuated Enclosure / Powder coated aluminum
- Remote Oil Filter Kits
- 50 Cycle Output
- Custom Chrome Packages
- Spare Parts Kit
- Custom Front PTO

2880 Hammondville Road  
Pompano Beach, FL 33069  
Tel: (954) 979-5899  
Fax: (954) 979-4349

900 Industrial Park Road #10  
Deep River, CT 06417  
Tel: (860) 526-9773  
Fax: (860) 526-2090

